



APT-X NADAJNIK ODBIORNIK BLUETOOTH  
APT-X BLUETOOTH PRJÍMAČ S VYSÍLAČEM  
APT-X BLUETOOTH SENDEMPFÄNGER

B3

User Manual | Instrukcja Obsługi | Uživatelská Příručka | Benutzerhandbuch  
(Manual Original) | (Instrukcja obsługi oryginalna) | (Originalní návod k použití) | (Originalanleitung)

Contents/zawartość  
obsah/Inhalt

English ----- 01~10  
Polish ----- 11~20  
Czech ----- 21~30  
German ----- 31~40

1. Product description

|     |  |
|-----|--|
| No. | Name   |
| A   | Working status indicator   |
| B   | AUX 3.5MM audio interface (audio input/output)   |
| C   | Optical fiber output interface (SPDIF OUT) in CRX mode   |
| D   | Optical input interface (SPDIF IN) in D TX mode  |
| E   | TYPE-C charging port   |
| F   | Up/Down (click) button, long press the button to increase/decrease volume. Note: in RX mode                                      |
| G   | Play/Pause button (click). Note: in RX mode  |
| H   | Pairing button, click to connect back, double-click to search for pairing.   |
| I   | RX/TX mode switch (RX: receiving mode TX: transmitting mode). Note: Toggle this switch to switch the working mode of the device. |
| J   | Power switch of the device (the interval between on/off should not be less than 3S)  |
| K   | Connection status indicator  |
| L   | Microphone hole  |

EN

Definition of LED Indicators:

| LED light status  | device status   |
|---|---|
| * lights on   | When the device is charging, it will automatically turn off when fully charged                        |
| * light flashes   | Device low battery alarm, charging can be released  |
| *TX lights on   | The device is in TX transmit mode   |
| *RX lights on   | The device is in RX receive working mode  |
| *APT.X, L.L, HD, AD, SBC, AAC lights on                             | The device CODEC mode corresponds to work in aptX, aptX Low Latency, aptX HD, aptX Adaptive, SBC, AAC |
| *AUX lights on  | The device works in AUX audio mode  |
| *OPT lights on  | The device works in SPDIF audio mode  |
| The connection status light blinks blue and green alternately       | In RX mode, pairing state   |
| The blue light of the connection status light flashes rapidly       | In TX mode, pairing search state  |
| Connection status light blue light is always on                     | The device has been connected successfully 1 bluetooth device   |
| The connection status light is solid green                          | The device has been successfully connected to 2 bluetooth devices                                     |
| The blue light of the connection status light flashes once every 1S | Device connection status  |
| The blue light of the connection status light flashes once every 2S | Standby state, double-click to enter pairing search state   |

2. Function operation

- Turn on/off (the interval between on/off should not be less than 3S)**  
Turn the power switch of the device to the ON end, the LED light will light up, and the device will be turned on.  
Turn the power switch of the device to the OFF end, the LED light goes out, and the device is turned off.
- Device reconnection/pairing search status**  
When the device is turned on, the device automatically enters the connection back and pairing search state.
- Quickly enter the pairing state**  
After the device is powered on, double-click the button continuously to quickly enter the pairing search state.
- Clear paired devices:**  
When the device is turned on, press and hold the button for 8 seconds, all LED lights will light up at the same time, and the paired device will be cleared successfully.
- AUX/SPDIF mode automatic switching:**  
The device audio adopts the automatic switching method, and the device defaults to SPDIF. When you plug in the AUX interface audio cable, it will automatically switch to AUX, and you can use AUX or SPDIF mode according to your preference.  
In SPDIF mode, the device is plugged into the SPDIF IN port and implements the TX (transmit) function. Plug into SPDIF OUT port for RX (receive) function.  
Note: When using the SPDIF audio mode, please do not plug the audio cable into the AUX interface. After plugging the audio cable into the AUX port, the device will switch to the AUX audio mode.
- Key Function**  
In RX mode: Click button up/down, long press +/ volume Click the button to play or pause music, double click to call back When an call comes, click to answer/hang up, long press to reject the call Click the button to connect back to the device Double-click the button to quickly enter the pairing state

In TX mode: Long press +/Volume Click Mute or Resume Double click to switch audio encoding Click the button to connect back to the device Double-click the button to quickly enter the pairing state

**7) Automatic shutdown function**  
When the device is not connected, it will automatically shut down after 10 minutes, and it needs to be turned on and off again to wake up.

**8) Low battery alarm prompt**  
When the battery is low, the charging red light flashes and an alarm sounds; if the battery is lower than 3.0V, it will automatically shut down.

**9) Audio encoding (TX mode)**  
During TX connection playback, double-click the button to switch the audio CODEC (you can switch between the current level and the next level, SBC cyclically).

**10) Game Mode (RX Mode)**  
During RX mode connection and playback, press and hold the pairing button for 2 seconds to switch to low-latency game mode.

**RX receive mode:**  
Mobile phones, computers, PDA, etc. are connected to the device through the Bluetooth function, and the music is transferred to the audio device with the AUX audio input interface through the Bluetooth receiving function of the device.

**Steps:**  
A. Put the RX/TX switch on the side of the device to the RX end, turn on the device power switch and turn it to the ON end. When the device is turned on, the "RX" indicator lights up.  
B. Double-click the button, the device quickly enters the pairing state (connection status light - blue and green lights flash alternately).  
C. Please insert the optical fiber cable into the SPDIF OUT RX interface of the device, the "OPT" light on the device is on, and the other end of the optical fiber cable is inserted into the optical input interface of the audio equipment in the home.

(Note: When using the SPDIF audio mode, please do not plug the audio cable into the AUX port. After the audio cable is plugged into the AUX port, the device will switch to the AUX audio mode.)  
If you are using the AUX audio interface, please insert the 3.5MM audio cable into the AUX interface on the device, the "AUX" light on the device is on, and the other end of the audio cable is inserted into the audio input interface of the audio equipment in the home.  
D. Turn on the Bluetooth function of the mobile phone, click to search for Bluetooth devices, select and click to connect the device name " B3 " in the Bluetooth list.  
E. After the connection is successful, the device name " B3 " in the Bluetooth list on the device is always on.  
Note: When the device is playing music, the audio indicator lights correspond to aptX, HD (aptX HD), AD (aptX Adaptive), SBC, and AAC.  
**TX transmit mode:**  
This device can be used with a TV to wirelessly forward the sound to a Bluetooth device (Bluetooth headset) or a Bluetooth speaker.  
**Steps:**  
A. Turn on the Bluetooth speaker or Bluetooth headset waiting to be connected and put it in the pairing state.  
B. Put the RX/TX switch on the side of the transmitter device to the TX end, turn on the power switch of the device and turn it to the ON end. When the device is turned on, the "TX" indicator lights up.  
C. Double-click the button, the device quickly enters the pairing search state (connection status light - blue light flashes quickly).  
D. Insert the optical fiber cable into the SPDIF IN TX interface on the transmitter device, the "OPT" light on the device is on, and the other end of the optical fiber cable is inserted into the TV output interface in the home.  
Note: When using the SPDIF audio mode, please do not plug the audio cable into the AUX port. After the audio cable is plugged into the AUX port, the device will switch to the AUX audio mode.  
If you are using the AUX audio interface, please insert the 3.5MM audio cable into the AUX interface on the device, the "AUX" light on the device is on, and the other end of the audio cable is inserted into the TV audio output interface in the home.

E. The blue light of the connection status light on the device flashes rapidly, searching for a Bluetooth device (Bluetooth headset or speaker). Please connect this product and a Bluetooth device (such as a Bluetooth headset) within 1M.  
F. After the product is successfully paired and connected, the blue light of the connection status light is always on.  
Note: When the device transmits music, the audio indicator lights correspond to aptX, L.L (aptX Low Latency), HD (aptX HD), AD (aptX Adaptive), and SBC.  
Note:  
① Different Bluetooth devices (such as Bluetooth headsets) have different time to search for connection due to differences in the scheme and protocol used. If the connection is not successful for a long time, you can restart the device and try to connect again.  
② The blue status light on the TX mode device flashes rapidly, which is the state of searching for Bluetooth devices (Bluetooth headset or speakers).  
③ It is recommended to put the Bluetooth speaker or Bluetooth headset in the pairing state first, and then open the device to search for pairing, which can improve the connection speed.  
④ If the sound is abnormal after connecting to the Bluetooth device (no sound, freeze, noise), you can double-click the button to switch the audio codec to SBC.  
⑤ When the TV is connected with optical fiber, please check the audio settings on the TV and set the audio output mode to PCM mode, otherwise the audio will not be able to make sound through the Bluetooth adapter!  
**TX launch one-to-two function:**  
A. Refer to the above connection steps to connect to the A Bluetooth device (Bluetooth headset or speaker).  
B. After the Bluetooth device No. A (Bluetooth headset or speaker) is successfully connected, please turn on the Bluetooth device No. B (Bluetooth headset or speaker) and put it in the state of waiting for pairing connection.  
C. Double-click the button, the device quickly enters the pairing search state (the blue light of the connection status light flashes rapidly), and starts to search for the Bluetooth device No. B (Bluetooth headset or speaker). After searching for the Bluetooth device No. B, it will automatically connect.  
D. After the connection is successful, the green light of the connection status light on the device lights up, and the Bluetooth device A and B (Bluetooth earphones or speakers) emit sound at the same time.

Note: ① If you cannot search and connect to Bluetooth device B, you can double-click the button to switch the audio codec to SBC.  
② After connecting to the Bluetooth device, the sound is abnormal (no sound, freeze, noise), you can double-click the button to switch the audio code to SBC.  
**3 Charge**  
When the product is in use, the charging red light flashes, indicating that the device is low in power and needs to be charged.  
A. Insert the Type-C charging cable into the product charging port, and connect the other end to the USB-V power output port (such as mobile phone charger, computer USB port).  
B. The charging time is about 3 hours. The red light stays on during charging, and goes out when charging is complete.  
Note:  
① When the battery power is too low or the quality of the charging power supply is poor, it may cause current noise in the device.  
② During charging, when the battery is about to be fully charged, there may be charging back flow noise, which can be solved by removing the charging cable.  
**4 Specifications**  
Bluetooth version: V5.2  
Supported bluetooth protocols: RX: AZDP AVRCP HSP HFP TX: AZDP TX: aptX Adaptive / aptX HD / aptX LL / aptX / SBC  
Bluetooth frequency: 2402 to 2480 MHz  
Transmission distance: >10m (line of sight, no obstructions)  
Charging method: Type-C USB, 5V/0.5A  
Working time: RX >20h TX >12h  
Charging time: about 3h  
Charging voltage: DC 5V  
Audio input/output: SPDIF / 3.5mm audio interface  
Audio CODEC: TX: aptX Adaptive / aptX HD / aptX LL / aptX / SBC  
RX: aptX Adaptive / aptX HD / aptX / AAC / SBC  
Material: ABS  
Dimensions: 67 x 77 x 19 mm  
Net weight: net: 93g

**Declaration of Conformity**  
Hereby Mozos Sp. z o.o. declares that the Mozos B3 devices comply with the essential requirements and other relevant provisions of the following directives: RED 2014/53/EU, Test standards: EN IEC 62368-1:2020+A11:2020, EN 62479:2010, EN 55063:2017, ETSI EN 301 489-1 V2.2.3 (2019-11), ETSI EN 301 489-1 V3.2.4 (2020-09), ETSI EN 300 328 V2.2.2 (2019-07). The full CE declaration of conformity can be found at [www.mozos.pl/declaracje](http://www.mozos.pl/declaracje).  
The use of the WEEE symbol (crossed-out bin) means that this product may not be treated as household waste. Proper disposal of used equipment allows you to avoid threats to human health and the natural environment resulting from the possible presence of hazardous substances, mixtures and components in the equipment, as well as improper storage and processing of such equipment. Selective collection also allows for the recovery of materials and components from which the device was manufactured. For details on recycling this product, please contact the retailer where you purchased it or your local authority. Made in China for: Mozos sp. z o.o. Sokratesa 13/37, 01-909 Warszawa NIP: PL 118229831 BDO registration number: 000558288.

Producer/Productent/Vyrobce/Hersteller: Mozos Sp. z o.o. Sokratesa 13/37, 01-909 Warszawa NIP: PL 118229831 BDO:000558288; serwis@mozos.pl; www.mozos.pl  
+48508439793; Made in China, Wyprodukowano w ChRL, Wyrobiono w Chin, Hergestellert in China

**Safety Card**  
**1. Product and Manufacturer Identification**  
Product Name: As specified on the packaging, label, or instructions  
Model: As specified on the packaging, label, or instructions  
Manufacturer: Mozos Sp. z o.o., Sokratesa 13/37, 01-909, Warsaw, NIP: PL118229831; BDO: 000558288; Manufactured in China  
Contact: Tel.: +48 508 439 793, Email: serwis@mozos.pl  
Batch/Serial Number: Not applicable  
General Safety Conditions: Products comply with the General Product Safety Regulation (GPSR) (EU Regulation 2023/988, Art. 7 of Section II, and EU Regulation 2019/1020)  
Technical and Mechanical Data: Product description and CE compliance details on the manufacturer's website  
Assembly Instructions and Usage: In the product packaging or on the manufacturer's website: www.mozos.pl/instrukcje  
Chemical Substances: Not applicable  
**2. Safe Usage Guidelines**  
Assembly: Connect the transmitter/receiver using the supplied cables to the intended devices. Ensure stable positioning to prevent disconnection.  
Placement: Keep away from water, heat sources, and direct sunlight. Ensure good airflow and avoid enclosed spaces.  
Intended Use: For transmitting or receiving Bluetooth audio signals with compatible audio devices.  
Weight Limit: Not applicable  
Handling and Storage: Store in a dry, cool environment when not in use. Disconnect cables before storage.  
Stability: Place on a flat, stable surface. Do not hang or suspend the unit from cables.  
Compatibility: Compatible with APX\* and standard Bluetooth-enabled devices. Verify with your device specifications.  
Regular Inspection: Check ports and cables regularly for dust or damage.  
Children & Pets: Keep out of reach of children and pets to avoid choking hazard or damage.  
**3. Warnings**  
Risk of Injury: Do not insert foreign objects into ports.  
Risk of Falling: Avoid placing on unstable or narrow surfaces.  
Risk of Damage: Improper wiring or cable usage may damage internal components.  
Risk of Tripping: Over not applicable.  
Pinching Hazard: Not applicable.  
Fire Hazard: Do not expose to open flame or overheating.  
Improper Assembly Hazard: Incorrect setup may result in malfunction or no signal transmission.  
**4. Maintenance and Disposal Instructions**

Maintenance: Keep the surface clean and dry. Avoid moisture around connectors.  
Regular Inspection: Verify operational status and cable condition periodically.  
Cleaning: Wipe gently with a dry cloth. Avoid the use of liquid cleaners.  
Storage: Store in original packaging or similar protective case.  
Disposal: Dispose of according to local electronic waste regulations.  
Recycling: Contribute to electronic recycling programs when available.  
Hazardous Materials: Not applicable.  
Donation & Reuse: Device can be reused if in good working condition.  
Environmental Release Measures: Not applicable.  
Personal Protection: Not applicable.  
Toxicological Information: No known toxic effects.  
Ecological Information: Product is not biodegradable.  
**5. Conformity Information**  
The product complies with the CE Directive: RED 2014/53/EU, Test standards: EN IEC 62368-1:2020+A11:2020, EN 62479:2010, EN 55063:2017, ETSI EN 301 489-1 V2.2.3 (2019-11), ETSI EN 301 489-1 V3.2.4 (2020-09), ETSI EN 300 328 V2.2.2 (2019-07).  
**6. Contact Information for Issues**  
For any doubts or product issues, please contact the technical support department:  
Tel.: +48 508 439 793  
Email: serwis@mozos.pl  
**7. First Aid Instructions**  
First aid measures aim to provide immediate support in health or life-threatening situations. These include ascertaining the condition of the victim, offering assistance according to established guidelines, and using first aid equipment that meets safety and quality requirements as per EU regulations, including the General Product Safety Regulation (GPSR). All actions should minimize risk to both the victim and the person providing aid, and their course is documented according to current regulations.  
In case of health or life-threatening danger, contact the emergency number: 112.  
**8. Transportation Information**  
The products are not classified as hazardous for transportation. Transport in enclosed means of transport.  
**9. Revision History**  
The information, advice, and guidelines contained in this document have been developed based on our knowledge, research, experience, and on good faith. We are not responsible for the consequences of improper or incorrect use of our products. Every user of this material should ensure in every possible way, including by testing the final product in appropriate conditions, that the provided materials are suitable for achieving the intended purposes.

1,1s produktu

|    |  |
|----|--|
| Nr | Nazwa  |
| A  | Wskaźnik stanu pracy   |
| B  | Interfejs audio AUX 3.5MM (wejście/wyjście audio)  |
| C  | Interfejs wyjścia światłowodowego (SPDIF OUT) w trybie C RX  |
| D  | Interfejs wejścia optycznego (SPDIF IN) w trybie D TX  |
| E  | Port ładowania TYPE-C  |
| F  | Przycisk góra/dół (kliknięcie), długie naciśnięcie przycisku zwiększa/zmniejsza głośność. Uwaga: w trybie RX                             |
| G  | Przycisk odtwarzania/pauzy (kliknięcie). Uwaga: w trybie RX  |
| H  | Przycisk parowania, kliknij, aby połączyć z powrotem, kliknij dwukrotnie, aby wyszukać parowania   |
| I  | Przełącznik trybu RX/TX (RX: tryb odbierania TX: tryb nadawania). Uwaga: Przełącz ten przełącznik, aby przełączyć tryb pracy urządzenia. |
| J  | Przełącznik zasilania urządzenia (przerwa między włączeniem/wyłączeniem nie powinna być krótsza niż 3S)                                  |
| K  | Wskaźnik stanu połączenia  |
| L  | Otwór mikrofonu  |

PL

Definicja wskaźników LED:

| Status kontrolki LED                                   | Stan urządzenia  |
|--|--|
| * świeci się   | Urządzenie jest ładowane, wyłącz się automatycznie po pełnym naładowaniu                                 |
| * miga   | Alarm niskiego poziomu naładowania baterii, ładowanie może zostać przerwane                              |
| *TX świeci się   | Urządzenie pracuje w trybie nadawania TX   |
| *RX świeci się   | Urządzenie pracuje w trybie odbioru RX   |
| *APT.X, L.L, HD, AD, SBC, AAC świeci się               | Tryb CODEC urządzenia odpowiada pracy w trybie: aptX, aptX Low Latency, aptX HD, aptX Adaptive, SBC, AAC |
| *AUX świeci się  | Urządzenie działa w trybie audio AUX   |
| *OPT świeci się  | Urządzenie działa w trybie audio SPDIF   |
| Kontrolka stanu połączenia miga na zielono i niebiesko | W trybie RX, stan parowania  |
| Niebieska kontrolka stanu połączenia                   | W trybie TX, stan wyszukiwania parowania   |
| Niebieska kontrolka stanu połączenia świeci się zawsze | Urządzenie zostało pomyślnie połączone z 1 urządzeniem bluetooth   |
| Kontrolka statusu połączenia świeci się na zielono     | Urządzenie zostało pomyślnie połączone z 2 urządzeniami bluetooth  |
| Niebieska kontrolka stanu połączenia miga raz na 1s    | Status połączenia urządzenia   |
| Niebieska kontrolka stanu połączenia miga raz na 2s.   | Stan gotowości, aby przejść do stanu wyszukiwania parowania  |

2. Działanie funkcji

- Włączanie/wyłączenie (przerwa między włączeniem/wyłączeniem nie powinna być krótsza niż 3 sekundy)**  
Ustaw przełącznik zasilania urządzenia w pozycji ON, dioda LED zaświeci się, a urządzenie zostanie włączone.  
Ustaw przełącznik zasilania urządzenia w pozycji OFF, dioda LED zgśnie, a urządzenie zostanie wyłączone.
- Stan wyszukiwania połączenia i parowania urządzenia**  
Po włączeniu urządzenia automatycznie przechodzi ono w stan ponownego połączenia i wyszukiwania parowania.
- Szybkie przejście do stanu parowania**  
Po włączeniu urządzenia należy dwukrotnie kliknąć przycisk, aby sposób ciągły, aby szybko przejść do stanu wyszukiwania parowania.
- Usuwanie sparowanych urządzeń:**  
Gdy urządzenie jest włączone, nacisnij i przytrzymaj przycisk przez 8 sekund, wszystkie diody LED zaświecą się w tym samym czasie, a sparowane urządzenie zostanie pomyślnie wyłączone.
- Automatyczne przełączanie trybu AUX/SPDIF:**  
Urządzenie audio przyjmuje metodę automatycznego przełączania, a urządzenie domyślnie przełącza się na SPDIF. Po podłączeniu kabla audio interfejsu AUX urządzenie automatycznie przełącza się w tryb AUX, a użytkownik może korzystać z trybu AUX lub SPDIF zgodnie z własnymi preferencjami.  
W trybie SPDIF urządzenie jest podłączone do portu SPDIF IN i realizuje funkcję TX (nadawania). Podłącz do portu SPDIF OUT, aby uzyskać funkcję RX (odbioru).  
Uwaga: Podczas korzystania z trybu audio SPDIF nie należy podłączać kabla audio do interfejsu AUX. Po podłączeniu kabla audio do portu AUX, urządzenie przełączy się w tryb audio AUX.
- Klawisz funkcji**  
Kliknij przycisk w górę/dół, długie naciśnięcie +/ głośność Aby nadzielić połączenie, kliknij, aby odebrać/rozłączyć, nacisnij długo, aby odrzucić połączenie  
Kliknij dwukrotnie przycisk, aby przejść do powrotu z urządzeniem Kliknij dwukrotnie przycisk, aby szybko wejść w stan parowania

w trybie TX: Długie naciśnięcie +/Volume Kliknij Mute lub Resume Podwójne kliknięcie, aby przełączyć kodowanie audio Podwójne kliknięcie, aby połączyć się z powrotem z urządzeniem

**7) Funkcja automatycznego wyłączenia**  
Gdy urządzenie nie jest podłączone, wyłącz się automatycznie po 10 minutach, a w celu wyłączenia należy ponownie włączyć i wyłączyć.

**8) Alarm niskiego poziomu naładowania baterii**  
Gdy poziom naładowania baterii jest niski, czerwona kontrolka ładowania miga i włącza się alarm; jeśli poziom naładowania baterii jest niższy niż 3.0 V, urządzenie wyłączy się automatycznie.

**9) Przełączanie kodowania audio (tryb TX)**  
Podczas odtwarzania połączenia TX, kliknij dwukrotnie przycisk, aby przełączyć kodak audio (można przełączać między bieżącym poziomem a następnym poziomem, SBC cyklicznie).

**10) Tryb tryb (tryb RX)**  
Podczas połączenia i odtwarzania w trybie RX, nacisnij i przytrzymaj przycisk parowania przez 2 sekundy, aby przełączyć na tryb tryb o niskim opóźnieniu.

**Tryb odbioru RX:**  
Telefony komórkowe, komputery, PDA y itp. są podłączone do urządzenia za pośrednictwem funkcji Bluetooth, a muzyka jest przesyłana do urządzenia audio z interfejsem wejściowym audio AUX za pośrednictwem funkcji odbioru Bluetooth urządzenia.

**Kroki:**  
A. Ustaw przełącznik RX/TX na z boku urządzenia w pozycji RX, włóż przełącznik zasilania urządzenia i ustaw go w pozycji ON. Po włączeniu urządzenia zawiąsanie się wskaźnik "TX".  
B. Kliknij dwukrotnie przycisk, urządzenie szybko przejdzie w stan wyszukiwania parowania (kontrolka stanu połączenia - niebieska kontrolka miga szybko).  
C. Podłącz kabel światłowodowy do interfejsu SPDIF IN TX w urządzeniu nadawczym, kontrolka "OPT" na urządzeniu zaświeci się, a drugi koniec kabla światłowodowego zostanie podłączony do interfejsu wyjścia audio telewizora w domu.  
Uwaga: W przypadku korzystania z trybu audio SPDIF nie należy podłączać kabla audio do portu AUX. Po podłączeniu kabla audio do portu AUX, urządzenie przełączy się w tryb audio AUX.

(Uwaga: W przypadku korzystania z trybu audio SPDIF nie należy podłączać kabla audio do portu AUX. Po podłączeniu kabla audio do portu AUX, urządzenie przełączy się w tryb audio AUX.)  
W przypadku korzystania z interfejsu audio AUX, należy podłączyć kabel audio 3.5MM do interfejsu AUX w urządzeniu, kontrolka "AUX" na urządzeniu zaświeci się, a drugi koniec kabla audio zostanie podłączony do interfejsu wyjścia audio telewizora w domu.  
D. Włącz funkcję Bluetooth w telefonie komórkowym, kliknij, aby wyszukać urządzenia Bluetooth, wybierz i kliknij, aby podłączyć urządzenie o nazwie " B3 " na liście Bluetooth.  
E. Po pomyślnym nawiązaniu połączenia, niebieski światło statusu połączenia na urządzeniu będzie zawsze włączone.  
Uwaga: Gdy urządzenie przesyła muzykę, wskaźniki audio odpowiadają aptX, LL (aptX Low Latency), HD (aptX HD), AD (aptX Adaptive) i SBC.  
**Tryb transmisji TX:**  
To urządzenie może być używane z telewizorem do bezprzewodowego przesyłania dźwięku do urządzenia Bluetooth (zestaw słuchawkowy Bluetooth) lub głośnika Bluetooth.  
**Kroki:**  
A. Włóż głośnik Bluetooth lub zestaw słuchawkowy Bluetooth oczekujący na połączenie i ustaw go w stanie parowania.  
B. Ustaw przełącznik RX/TX z boku urządzenia nadawczego w pozycji TX, włóż przełącznik zasilania urządzenia i ustaw go w pozycji ON. Po włączeniu urządzenia zawiąsanie się wskaźnik "TX".  
C. Kliknij dwukrotnie przycisk, urządzenie szybko przejdzie w stan wyszukiwania parowania (kontrolka stanu połączenia - niebieska kontrolka miga szybko).  
D. Podłącz kabel światłowodowy do interfejsu SPDIF IN TX w urządzeniu nadawczym, kontrolka "OPT" na urządzeniu zaświeci się, a drugi koniec kabla światłowodowego zostanie podłączony do interfejsu wyjścia audio telewizora w domu.  
Uwaga: W przypadku korzystania z trybu audio SPDIF nie należy podłączać kabla audio do portu AUX. Po podłączeniu kabla audio do portu AUX, urządzenie przełączy się w tryb audio AUX.)  
W przypadku korzystania z interfejsu audio AUX, należy podłączyć kabel audio 3.5MM do interfejsu AUX w urządzeniu, kontrolka "AUX" na urządzeniu zaświeci się, a drugi koniec kabla audio zostanie podłączony do interfejsu wyjścia audio telewizora w domu.  
D. Po pomyślnym nawiązaniu połączenia zawiąsanie się zielona kontrolka stanu połączenia na urządzeniu, a urządzenie Bluetooth A i B (słuchawki lub głośniki Bluetooth) wyemitują dźwięk w tym samym czasie.

E. Niebieska kontrolka stanu połączenia na urządzeniu miga szybko, wyszukując urządzenia Bluetooth (zestaw słuchawkowy Bluetooth lub głośnik). Podłącz ten produkt i urządzenie Bluetooth (takie jak zestaw słuchawkowy Bluetooth) w odległości do 1M.  
F. Po pomyślnym sparowaniu i podłączeniu produktu, niebieski światło kontrolki stanu połączenia jest zawsze włączone.  
Uwaga: Gdy urządzenie przesyła muzykę, wskaźniki audio odpowiadają aptX, LL (aptX Low Latency), HD (aptX HD), AD (aptX Adaptive) i SBC.  
**3. Ładowanie**  
Gdy produkt jest używany, czerwona kontrolka ładowania miga, wskazując, że poziom naładowania urządzenia jest niski i należy naładować.  
A. Podłącz kabel ładowany typu C do portu ładowania produktu, a drugi koniec do portu wyjściowego zasilania USB 5 V (np. ładowarki telefonu komórkowego, portu USB komputera).  
B. Czas ładowania wynosi około 3 godzin. Czerwona dioda świeci się podczas ładowania i gasnie po jego zakończeniu.  
Uwaga:  
1. Jeśli poziom naładowania baterii jest zbyt niski lub jakość zasilania ładowania jest niska, może to powodować zakłócenia prądu w urządzeniu.  
2. Podczas ładowania, gdy bateria jest blisko pełnego naładowania, może pojawić się szum ładowania wstecznego, który można wyeliminować poprzez odłączenie kabla ładowania.  
**4. Specyfikacja**  
Wersja Bluetooth: V5.2  
Obsługiwane protokoły Bluetooth: RX: AZDP AVRCP HSP HFP TX: AZDP Zasięg transmisji: >10m (w linii prostej, bez przeszkód)  
Częstotliwość Bluetooth: 2402 do 2480 MHz  
Bateria: 600mAh  
Materiał: ABS  
Czas pracy: RX >20h TX >12h  
Czas ładowania: około 3h  
Waga netto/zestaw: 93g

Uwaga: ① Jeśli nie można wyszukać i połączyć się z urządzeniem Bluetooth B, można dwukrotnie kliknąć przycisk, aby wyszukać i połączyć się ponownie. Jeśli połączenie nie powiodzie się przez dłuższy czas, można ponownie uruchomić urządzenie i spróbować połączyć się ponownie lub wyłączyć oczekujące urządzenia Bluetooth, aby uniknąć problemu niewłaściwego połączenia.  
② Jeśli po nawiązaniu połączenia z urządzeniem Bluetooth dźwięk jest nieprawidłowy (brak dźwięku, zawieszanie, szum), można dwukrotnie kliknąć przycisk, aby przełączyć kod audio na SBC.  
**3. Ładowanie**  
Gdy produkt jest używany, czerwona kontrolka ładowania miga, wskazując, że poziom naładowania urządzenia jest niski i należy naładować.  
A. Podłącz kabel ładowany typu C do portu ładowania produktu, a drugi koniec do portu wyjściowego zasilania USB 5 V (np. ładowarki telefonu komórkowego, portu USB komputera).  
B. Czas ładowania wynosi około 3 godzin. Czerwona dioda świeci się podczas ładowania i gasnie po jego zakończeniu.  
Uwaga:  
1. Jeśli poziom naładowania baterii jest zbyt niski lub jakość zasilania ładowania jest niska, może to powodować zakłócenia prądu w urządzeniu.  
2. Podczas ładowania, gdy bateria jest blisko pełnego naładowania, może pojawić się szum ładowania wstecznego, który można wyeliminować poprzez odłączenie kabla ładowania.  
**4. Specyfikacja**  
Wersja Bluetooth: V5.2  
Obsługiwane protokoły Bluetooth: RX: AZDP AVRCP HSP HFP TX: AZDP Zasięg transmisji: >10m (w linii prostej, bez przeszkód)  
Częstotliwość Bluetooth: 2402 do 2480 MHz  
Bateria: 600mAh  
Materiał: ABS  
Czas pracy: RX >20h TX >12h  
Czas ładowania: około 3h  
Waga netto/zestaw: 93g

**Deklaracja zgodności**  
Niniejszym Mozos Sp. z o.o. oświadcza, że urządzenia Mozos B3 są zgodne z zasadniczymi wymogami oraz innymi stosownymi postanowieniami poniżej wymienionych dyrektyw: RED 2014/53/EU, Standardy testowe: EN IEC 62368-1:2020+A11:2020, EN 62479:2010, EN 55063:2017, ETSI EN 301 489-1 V2.2.3 (2019-11), ETSI EN 301 489-1 V3.2.4 (2020-09), ETSI EN 300 328 V2.2.2 (2019-07). Pełna deklaracja zgodności CE znajduje się na stronie [www.mozos.pl/declaracje](http://www.mozos.pl/declaracje).  
Użycie symbolu WEEE (przekreślony kosz) oznacza, że niniejszy produkt nie może być traktowany jako odpad domowy. Prawidłowa użycia zużytego sprzętu pozwala uniknąć zagrożenia dla zdrowia i środowiska naturalnego, wynikającego z możliwości recyklingu i sprężenia niebezpiecznych substancji, mieszanin oraz części składowych, a także niewłaściwego składowania i przetwarzania takiego sprzętu. Zbiórka selektywna pozwala na odzyskanie materiałów i komponentów, z których wyprodukowane było urządzenie. W celu uzyskania szczegółowych informacji dotyczących recyklingu niniejszego produktu należy skontaktować się z punktem sprzedaży detalicznej, w którym dokonano zakupu, lub organem władzy lokalnej. Wyprodukowano w Chinach dla: Mozos sp. z o.o. Sokratesa 13/37 01-909 Warszawa NIP: PL 118229831 Numer rejestrowy BDO: 000558288.

Producer/Productent/Vyrobce/Hersteller: Mozos Sp. z o.o., Sokratesa 13/37, 01-909 Warszawa NIP: PL 118229831 BDO:000558288; serwis@mozos.pl; www.mozos.pl  
+48508439793; Made in China, Wyprodukowano w ChRL, Wyrobiono w Chin, Hergestellert in China

**Karta Bezpieczeństwa**  
**1. Identyfikacja Produktu i Producenta**  
Nazwa Produktu: Zgodnie z informacjami na opakowaniu, etykiecie lub w instrukcji obsługi.  
Model: Zgodnie z informacjami na opakowaniu, etykiecie lub w instrukcji.  
Producent: Mozos Sp. z o.o., Sokratesa 13/37, 01-909, Warszawa, NIP: PL118229831; BDO: 000558288; Wyprodukowano w Chinach  
Kontakt: Tel.: +48 508 439 793, Email: serwis@mozos.pl  
Numer partii / numer seryjny: Nie dotyczy  
Opisne warunki bezpieczeństwa: Produkt zgodne z Rozporządzeniem o Ogólnym Bezpieczeństwie Produktów (GPSR) (Rozporządzenie UE 2023/988, art. 7 sekcji II oraz Rozporządzenie UE 2019/1020)  
Dane techniczne i dane mechaniczne: Opis produktu oraz informacje o zgodności CE dostępne na stronie internetowej producenta  
Instrukcja montażu i użytkowania: W opakowaniu produktu lub na stronie internetowej producenta [www.mozos.pl/instrukcje](http://www.mozos.pl/instrukcje)  
Substancje chemiczne: Nie dotyczy  
**2. Wytyczne dotyczące odpowiedniego użytkowania**  
Montaż: Podłącz nadajnik/odbiornik za pomocą dostarczonych kabli do odpowiednich urządzeń. Zapewnij stabilne ustawienie, aby zapobiec rozłączeniu.  
Umieszczenie: Trzymaj z dala od wody, źródeł ciepła i bezpośredniego światła słonecznego. Zapewnij dobrą wentylację i unikaj zamkniętych przestrzeni.  
Przeznaczenie: Do przesyłania lub odbierania sygnałów audio przez Bluetooth ze zgodnymi urządzeniami audio.  
Limi wag: Nie dotyczy  
Obsługa i przechowywanie: Przechowywać w suchym, chłodnym miejscu. Odłączyć kable przed przechowaniem.  
Stabilność: Umieścić na płaskiej, stabilnej powierzchni. Nie wiszać ani nie zawieszać urządzenia na kablach.  
Regulacja głośności: Zgodność z urządzeniami z funkcją Bluetooth i standardem APT-X. Sprawdzić specyfikację urządzenia.  
Regulacja temperatury: Wyłączyć urządzenie i kable pod kątem krawki lub uszkodzeń.  
Dźwięk i zwierzęta: Przechowywać/poziomie zasilanie dźwięk i zwierząt w celu uniknięcia zagrożenia zadławieniem lub uszkodzeń.  
**3. Ostrzeżenia**  
Ryzyko obrażeń: Nie wkładaj ciał obcych do portów.  
Ryzyko wypadku: Nie wiszciec na niestabilnych lub wąskich powierzchniach.  
Ryzyko uszkodzenia: Nieumieszczenie nacięć lub użycie kabli może uszkodzić komponenty urządzenia.  
Ryzyko przewrócenia: Nie dotyczy.  
Ryzyko porażenia: Nie dotyczy.  
Ryzyko pożaru: Nie występuje na działanie otwartego ognia ani przegrzewania.  
Ryzyko niewłaściwego montażu: Nieprawidłowa instalacja może skutkować nieprawidłowym działaniem lub brakiem transmisji sygnału.

**4. Instrukcje dotyczące konserwacji i użycia**  
Konserwacja: Powierzchnię utrzymuj w czystości i suchości. Unikaj wilgoci w okolicy złączy.  
Czyszczenie: Wykonuj czyszczenie zgodnie z instrukcją obsługi.  
Czyścienie: Przecierać delikatnie suchą szmatką. Nie używaj środków czyszczących w płynie.  
Przechowywanie: Przechowywać w oryginalnym opakowaniu lub podobnym etui ochronnym.  
Recykling: Wykonaj zgodnie z lokalnymi przepisami dotyczącymi odpadów elektronicznych.  
Przekazanie i ponowne użycie: Można ponownie wykorzystywać, jeśli urządzenie działa prawidłowo.  
Środki zapobiegające uwolnieniu do środowiska: Nie dotyczy.  
Ochrona osobista: Nie dotyczy.  
Informacje ekologiczne: Produkt nie jest biodegradowalny.  
**5. Informacje o zgodności**  
Produkt jest zgodny z Dyrektywą