

Infinix

True Wireless Earphones Buds Neo

Model: XE26

User Manual

Hereby, INFINIX MOBILITY LIMITED.

Declares that this True Wireless Earphones is in compliance with the essential requirements and other relevant provisions of directive 2014/53/EU.

Please read this manual carefully before using this product.

1. What's In The Box

EN



Charging case X1



True Wireless Earbud X2




USB-C Cable X1



Eartips

2. Product Overview



- 1 Earbud Status Indicator
- 2 Multi-Function Button (MFB)
- 3 Microphone
- 4 Type-C Charging Port
- 5 Left Earbud
- 6 Right Earbud
- 7 Case Status Indicator

3. Using Your Earbuds

3.1 Remove the protective film

- 1 Protective film



3.2 CHARGING



Put the earbuds back to the charging case.



Fully charge the case.



Flash Red

Being charged



Steady Red

Fully charged

3.3 POWER ON/OFF

ON



- Take out the earbuds from the charging case and the earbuds will power on automatically.

OFF



- When the earbuds are outside the charging case and powered on, press and hold for 5 seconds on each earbud MFB button to power off.
- Put the earbuds back into the charging case and close the lid to power off automatically.

3.4 PAIRING



Earbuds will power on and enter pairing mode automatically when taking out the earbuds from charging case.

Earbuds Status Indicator

●	Rapidly flash green on both earbuds	TWS Pairing
● ●	Flash red and green alternatively	BT Pairing
●	Light Off	Connected Successfully

- Make sure the distance of the earbuds and your device is less than 1 metre/3.3 feet at the first time of connection.
- When turned on, the earbuds will automatically connect to the last connected device if available. If not, the earbuds will enter pairing mode.
- Under any abnormal condition, put the earbuds back into the charging case with the lid closed, then take out again after 15 seconds.

3.5 DOWNLOAD THE WELIFE APP



1. Scan the QR code or search your phone's app store to download the WELIFE app to discover more features or contact our support team.
2. Make sure your earbuds are powered on, then open the WELIFE app and tap the "AddDevice" button to pair the earbuds with the app.

※ Only for devices running Android 7.0 and later versions.

Experience Multiple EQ Modes:

Support Bass Booster, Treble Booster, Vocal Booster, Default mode. Choose the one that suits you best.

Quick Activation of Game Mode:

Enable Game Mode quickly in the app to achieve better synchronization of audio and video for an enhanced gaming experience.

Touch Controls Customization:

Discover or customize the functions triggered with earbuds touch controls. Answering call and controlling music are at your fingertips.

3.6 RESET



(Try the following steps if you fail pairing between two earbuds, or between earphones and device)

1. Clear pairing record between the earbuds and your device in the bluetooth pairing list on your device.
2. Take out the earbuds from the charging case, simultaneously tap four times and then long press on both MFB button within three seconds to clear the pairing record and enter the pairing mode automatically.

3.7 CONTROLS

MUSIC

	Tap twice on one earbud		Play/Pause
	Press and hold for 2 seconds on the left earbud		Previous Track
	Press and hold for 2 seconds on the right earbud		Next Track

CALL

 X2	Tap twice on one earbud	 	Answer/End a call
 2'	Press and hold for 2 seconds on one earbud		Reject

OTHER

 X3	Tap three times on the left earbud(only TWS mode)		Switch Game mode
 X3	Tap three times on the right earbud		Activate Voice Assistant
 X1	Tap once on the left earbud		Decrease the volume
 X1	Tap once on the right earbud		Increase the volume
 X4+5'	Tap four times and then long press the MFB button within three seconds on both earbuds(power on status)		Reset

4.Product Specification

Input	5V---500 mA
Speaker Driver	φ13mm×2
Battery Capacity	40mAh×2(earbuds), 500mAh(charging case)
Impedance	32Ω
Play-time	Up to 6 hours (Totally 28 hours with the charging case)
Charging Time	Approx. 1.5 hours(earbuds), 2.5 hours(charging case)

Talk time	Up to 4.5 hours
Bluetooth Range	10m/33ft
Rated Output Power	5mW
Frequency Response	20Hz-20KHz

CONSIDERATE HINTS

1. Do not turn up the volume to a fair high level constantly as this could shorten the service life of this product or impair your hearing.
2. When encounter any fault during operation, please cut off the power supply and disconnect the type-C cable to prevent further damage to the product or other components.
3. The Wireless transmission range or connectivity could be affected by low battery power. In that case, please recharge immediately.

ATTENTION

- use original or certified cables.
- Do not expose to the liquids.
- Do not disassemble.
- Avoid dropping.
- Avoid extreme temperatures.
- Do not use the product outdoors during a thunderstorm.
- Do not use any corrosive cleaner/oil to clean.

CAUTION

1. Use carefully with the earphone maybe excessive sound pressure from earphones and earphones can cause hearing loss.
2. Risk of explosion if battery is replaced by an incorrect type, dispose of used batteries according to the instructions.
 - disposal of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery, that can result in an explosion;

- leaving a battery in an extremely high temperature surrounding environment that can result in an explosion or the leakage of flammable liquid or gas;
 - a battery subjected to extremely low air pressure that may result in an explosion or the leakage of flammable liquid or gas.
- 3.The product shall only be connected to a USB interface Of version USB 2.0.
- 4.EUT Temperature: 0℃~+45℃(Standalone).0℃~+40℃(with adapter).
- 5.To prevent possible hearing damage, do not listen at high volume levels for long periods.
- 6.USB cable is shielded.

Frequency Range(RF):

BT:2402-2480MHz(TX/RX);

RF output power:

BT:0-10dBm



High sound pressure with hearing damage risk.
Do not listen at high volume levels for long periods.

EU DECLARATION OF CONFORMITY

in accordance with

Annex VI of Directive 2014/53/EU of the European Parliament and of the Council

1. For the following Radio equipment.

Model: XE26

Product: True Wireless Earphones

Trade name or Brand: Infinix

Software / Hardware number: V01/V01

- 2.Name and address of the manufacturer or his authorized representative:
Manufacturer: INFINI XMOBILITY LIMITED
Address:FLAT N 16/F BLOCK B UNIVERSAL INDUSTRIAL CENTRE 19-25
SHAN MEI STREET FOTAN NT HONGKONG
- 3.This declaration of conformity is issued under the sole responsibility of the Manufacturer.
- 4.Object of the declaration (identification of the radio equipment allowing traceability; it may include a colour image of sufficient clarity where necessary for the identification of the radio equipment):
- 5.The object of the declaration described above is in conformity with the relevant Union harmonization legislation: Directive 2014/53/EU (RED)
- 6.References to the relevant harmonised standards used or references to the other technical specifications in relation to which conformity is declared:
Article 3.1a Health:
EN 62479:2010
- Article 3.1a Electrical Safety:
EN 62368-1:2014+A11: 2017
EN IEC 62368-1:2020+A11:2020
- Article 3.1b:
ETSI EN 301 489-1 V2.2.3 (2019-11)
ETSI EN 301 489-17 V3.2.4 (2020-09)
- Article 3.2:
ETSI EN 300 328 V2.2.2(2019-07)
- 7.Notified Body Name: Eurofins Electrical and Electronic Testing NA, Inc.
Notified Body Number: 0980
Notified Body Assessment Performed: Module B/C on Article 3.1a, 3.1b, 3.2
Technical File Identification Number: N/A
- 8.Where applicable, description of accessories and components, including software, which allow the radio equipment to operate as intended and covered by the EU declaration of conformity: User instructions are provided in the User Manual. The Software and Hardware versions are specified above.

9. Additional information:

Referring to Article 10.2 of the Directive, this equipment is so constructed that it can be operated in all Member States, without infringing applicable requirements on the use of radio spectrum. Referring to Article 10.10 of the Directive, there are no restrictions on putting this equipment into service or of requirements for authorisation of use. Please refer to the User Manual for details.

On behalf of:

Manufacturer: INFINIX MOBILITY LIMITED

Address: FLAT N 16/F BLOCK B UNIVERSAL INDUSTRIAL CENTRE 19-25
SHAN MEI STREET FOTAN NT HONGKONG

(place and date of issue):Shenzhen, 2023-04-03

(name, function):Nengyong.Wu/ Manager

(signature): nengyong. wu

(Name and signature of person responsible)

Infinix

True Wireless Earphones Buds Neo

Model: XE26
Instrukcja obsługi

Niniejszym INFINIX MOBILITY LIMITED
deklaruje, że te słuchawki są zgodne z wymaganiami i innymi
stosownymi postanowieniami dyrektywy 2014/53/UE.
Przed rozpoczęciem korzystania ze słuchawek należy uważnie
przeczytać niniejszą instrukcję.

1. Zawartość opakowania

PL



1x etui ładujące



2x słuchawki True
Wireless Earbud





1x kabel USB-C



L S

wkładki douszne

2. O produkcie



- 1 Dioda pokazująca status słuchawek
- 2 Przycisk wielofunkcyjny (MFB)
- 3 Mikrofon
- 4 Złącze typu USB-C
- 5 Lewa słuchawka
- 6 Prawa słuchawka
- 7 Dioda pokazująca tryb pracy etui

3. Jak używać słuchawek

3.1 Usuń folię ochronną

- 1 Folia ochronna



3.2 Ładowanie słuchawek



Umieść słuchawki w etui ładującym



Naładuj etui do 100%



Czerwone światło migające

Ładowanie



Czerwone światło ciągle

Naładowane

3.3 Włączanie i wyłączanie



- Otwórz etui, słuchawki włączą się automatycznie.



- Jeśli słuchawki są poza etui, wystarczy nacisnąć i przytrzymać przez 5 sek. przyciski na obudowie.
- Umieść słuchawki w etui i zamknij klapkę. Słuchawki zostaną wyłączone i zaczną się ładować.

3.4 Parowanie



Słuchawki douszne włączą się i przejdą w tryb parowania automatycznie po ich wyjęciu słuchawek z etui-ładowarki.

Wskaźnik statusu słuchawek

●	Szybko migająca zielona dioda na obu słuchawkach	Parowanie TWS
● ●	Zielona i czerwona dioda migają naprzemiennie	Parowanie BT
●	Dioda zgasła	Parowanie się udało

- Upewnij się, że odległość między słuchawkami, a urządzeniem z którym chcesz je sparować jest przy pierwszym parowaniu mniejsza niż 1 metr.
- Po włączeniu słuchawki douszne automatycznie połączą się z ostatnim apamiętanym urządzeniem, jeśli jest ono dostępne. Jeśli nie, słuchawki wejdą w tryb parowania.
- W razie nieprawidłowości w parowaniu schowaj słuchawki do etui na 15 sek. i wyjmij je ponownie.

3.5 Pobierz aplikację Welife



1. Zeskanuj kod QR, aby szybko pobrać aplikację Welife. W niej ustawisz preferowane efekty audio, tryb wyciszania hałasu, znajdziesz obsługę klienta i znacznie więcej.
2. Włącz słuchawki douszne, następnie otwórz aplikację Welife i stuknij przycisk Dodaj urządzenie, aby połączyć aplikację ze słuchawkami (tylko dla urządzeń z systemem Android 7.0 lub wyższym).

Różne tryby equalizera:

Do wyboru mamy wiele ulepszeń, w tym Bass Booster, Treble Booster, Vocal Booster, itp.

Szybka aktywacja trybu gry:

Szybkie włączenie trybu gry w aplikacji służy do uzyskania lepszej synchronizacji dźwięku i obrazu, co przekłada się na lepsze wrażenia w grze.

Własna kontrola gestami:

Odkryj i korzystaj z własnych gestów sterujących. Dzięki interfejsowi dotykowemu masz pełną kontrolę w zasięgu dłoni.

3.6 Reset i ustawienia fabryczne



Wypróbuj następujące kroki, jeśli parowanie z urządzeniem lub między słuchawkami nie powiedzie się.

1. Wyczyść zapis parowania między słuchawkami dousznymi a urządzeniem w liście parowania Bluetooth na urządzeniu.
2. Wyjmij słuchawki z etui ładującego, stuknij jednocześnie cztery razy, następnie naciśnij długo oba przyciski MFB i trzymaj przez 3 sekundy aby wyczyścić zapis parowania i automatycznie przejść do trybu parowania.

3.7 Sterowanie

MUZYKA



Dwa stuknięcia w jedną słuchawkę

▶ || Graj/Pauzuj



2^o Naciśnij i przytrzymaj lewą słuchawkę przez 2 sek.

◀ Poprzednia ścieżka



2^o Naciśnij i przytrzymaj prawą słuchawkę przez 2 sek.

▶ Następną ścieżka

ROZMOWA

 X2	Dwa stuknięcia w jedną słuchawkę		Obiór i zakończenie połączenia
 2'	Dotknięcie i przytrzymanie jednej słuchawki przez 2 sekundy		Odrzucenie połączenia

INNE

 X3	Trzy stuknięcia na lewej słuchawce (tylko w trybie TWS)		Tryb gry
 X3	Trzy stuknięcia na prawej słuchawce		Aktywacja asystenta głosowego
 X1	Jedno stuknięcie lewej słuchawki		Ciszej
 X1	Jedno stuknięcie prawej słuchawki		Głośniej
 X4+5'	4 stuknięcia obu słuchawek i przytrzymanie przycisku przez 3 sekundy		Reset

4. Cechy urządzenia

Zasilanie	5V  500 mA
Głośnik	φ13 mm ×2
Baterie	40 mAh x2 (słuchawki), 500 mAh (etui)
Oporność	32Ω
Czas pracy	Do 6 godzin, 28 godzin z ładowaniem z etui
Czas ładowania	Ok. 1,5 godziny (słuchawki), Ok. 2,5 godziny (etui)

Czas rozmów	Do 4,5 godziny
Zasięg Bluetooth	10 m
Znamionowa moc wyjściowa	5 mW
Pasma	20 Hz - 20 KHz

Wskazówki dotyczące bezpieczeństwa

1. Nie należy używać długo wysokich poziomów głośności, ponieważ może to skrócić żywotność produktu lub uszkodzić słuch.
2. W przypadku napotkania jakiegokolwiek usterki podczas pracy, należy odłączyć zasilanie i odłączyć kabel, aby zapobiec uszkodzeniu produktu lub innych urządzeń.
3. Niski poziom naładowania baterii może mieć wpływ na zasięg bezprzewodowy. W takim przypadku należy ją niezwłocznie naładować.

UWAGA

Należy używać wyłącznie sprawdzonych kabli.

Nie wystawiać na działanie płynów.

Nie rozbierać.

Unikać uszkodzeń fizycznych.

Unikać ekstremalnych temperatur.

Nie używać produktu na zewnątrz podczas burzy.

Do czyszczenia nie używać żrących środków czyszczących/olejów.

Ostrożnie

1. Należy zachować ostrożność podczas korzystania ze słuchawek, ponieważ nadmierne ciśnienie akustyczne może spowodować uszkodzenie lub utratę słuchu.
2. Istnieje ryzyko porażenia prądem, jeśli bateria zostanie wymieniona na baterię nieprawidłowego typu.
 - Zużyte baterie należy utylizować zgodnie z instrukcjami.
 - Wrzucenie baterii do ognia lub gorącego piekarnika, mechaniczne

- uszkodzenie lub rozszczelnienie baterii może spowodować wybuch;
- Pozostawienie baterii w otoczeniu o bardzo wysokiej temperaturze może spowodować eksplozję lub wyciek łatwopalnego płynu lub gazu.
 - Bateria wystawiona na działanie bardzo niskiego ciśnienia może wybuchnąć albo stracić szczelność, co może prowadzić do wycieku łatwopalnego płynu i/lub gazu.
3. Etui może łączyć się przewodowo za pomocą interfejsu USB 2.0
 4. Temperatura EUT 0-45 °C (samodzielnie), 5 – 40 °C (z adapterem).
 5. Aby zapobiec możliwemu uszkodzeniu słuchu, nie słuchaj przy wysokim poziomie głośności przez długi czas.
 6. Przewód USB jest ekranowany.

Zakres częstotliwości (RF):

Bluetooth: 2402-2480 MHz (TX/RX);

Moc wyjściowa RF:

BT: 0-10 dBm



Wysokie ciśnienie akustyczne grozi uszkodzeniem słuchu.
Nie należy słuchać wysokich poziomów głośności przez dłuższy czas.

DEKLARACJA ZGODNOŚCI UE

Zgodnie z Załącznikiem VI do Dyrektywy 2014/53/EU Parlamentu Europejskiego i Rady Europy:

1. Dla następujących urządzeń radiowych:

Model: XE26

Produkt: Bezprzewodowe słuchawki douszne

Nazwa handlowa lub marka: Infinix

Numer oprogramowania i sprzętu: V01/V01

2. Nazwa i adres producenta lub jego autoryzowanego przedstawiciela:
Producent: INFINIX MOBILITY LIMITED
Adres: FLAT N 1 6/F BLOCK B UNIVERSAL INDUSTRIAL CENTRE
19-25 SHAN M EI STREET FOTAN NT HONGKONG
3. Niniejsza deklaracja zgodności została wydana na wyłączną odpowiedzialność na wyłączną odpowiedzialność Producenta.
4. Przedmiot deklaracji (identyfikacja urządzenia radiowego umożliwiającego śledzenie; może zawierać kolorowy obraz o wystarczającej wyrazistości tam, gdzie jest to konieczne do identyfikacji urządzenia radiowego):
5. Opisany powyżej przedmiot deklaracji jest zgodny z odpowiednimi unijnymi przepisami harmonizacyjnymi: Dyrektywa 2014/53/UE (RED).
6. Odniesienia do odpowiednich norm zharmonizowanych lub odniesienia do innych specyfikacji technicznych, w odniesieniu do których deklarowana jest zgodność.

Artykuł 3.1a Zdrowie:

EN 62479:2010

Artykuł 3.1a Bezpieczeństwo elektryczne:

EN62368-1:2014+A11 :2017

EN IEC 62368-1:2020+A11:2020

Artykuł 3.1b:

ETSI EN 301 489-1 V2.2.3 (2019-11)

ETSI EN 301 489-17 V3.2.4 (2020-09)

Artykuł 3.2:

ETSI EN 300 328 V2.2.2 (2019-07)

7. Powiadomiona instytucja: Eurofins Electrical and Electronic Testing NA, Inc. Numer: 0980.

Wykonane oceny: Moduł B/C w Artykule 3.1a, 3.1b, 3.2.

8. W stosownych przypadkach opis akcesoriów i komponentów, w tym oprogramowania, które umożliwiają działanie urządzenia radiowego zgodnie z przeznaczeniem są objęte deklaracją zgodności UE:
Instrukcje użytkownika znajdują się w podręczniku użytkownika. Wersje oprogramowania i sprzętu podano powyżej.

9. Informacje dodatkowe: Odnosząc się do artykułu 10.2 Dyrektywy, to urządzenie jest tak skonstruowane, że może być używane we wszystkich państwach członkowskich bez naruszania obowiązujących wymogów dotyczących wykorzystania widma radiowego.

Zgodnie z Artykułem 10.10 Dyrektywy, nie ma żadnych ograniczeń dotyczących oddawania tego sprzętu do użytku ani wymagań dotyczących autoryzacji użytkowania. Szczegółowe informacje znajdują się w instrukcji obsługi.

W imieniu:

Producent: INFINIX MOBILITY LIMITED

Adres: FLAT N 16/F BLOCK B UNIVERSAL INDUSTRIAL CENTRE 19-25
SHAN MEI STREET FOTAN NT HONGKONG

(miejsce i data) Shenzen 2023-04-03

(imię/nazwisko, funkcja) Nengyong Wu, Manager

(podpis) nengyong. wu

(nazwisko i podpis osoby odpowiedzialnej)